



## AVR GENERATOR

### GAV 2800

#### ADVANTAGES

- Safe regulation AVR Generator with 1 single-phase socket 230V.
- Supplies an automatically regulated output current to keep it constant
- Gas and motor acceleration automatically regulated by an AVR card according to the workload.
- 4 phase stable motor with head valves.
- Engine oil level security control .
- Low intake, noise and vibrations.
- Portable generator with transport wheels.
- Output tension indicator.
- Tubular structure in cradle shape to protect and transport the generator.



#### DATA SHEET

GENERATOR	
Regulation	AVR
Nominal voltage	230 V
Nominal current	11 A
Nominal power	2.5 kW
Maximum power	2.8 kW
DC Output, Voltage	12 Vdc
DC Output, Amperes	4.2 A
Frecuency	50 Hz
MOTOR	
Type	4T OHV
Cubic capacity	196 cm <sup>3</sup>
Start	Manual
Nominal power	3.8 HP
Gas capacity	15 L
Oil capacity	0.6 L
Autonomy	13 H
Noise power level	98 dB (A)
Size	60 x 46 x 46.5 cm
Weight	50 Kg

#### INCLUDES

- Transport rod
- Plug key
- Socket
- Rubber coated legs
- 2 wheels



PROFESSIONAL QUALITY  
[www.stayer.es](http://www.stayer.es)