



## GID GAS GENERATOR

### GID 2200 B

#### ADVANTAGES

- Generator with 100% stabilised inverter regulation with 1 single-phase 230V socket and a USB port.
- Safe connection to any type of device without harmful surges.
- Low consumption, noise and vibration.
- Output voltage indicator.
- Compact structure for protection and easy transport of the generator.



#### DATA SHEET

##### GENERATOR

Regulation **100% Inverter stabilized**

|                    |                |
|--------------------|----------------|
| Nominal voltage    | <b>230</b> V   |
| Rated current      | <b>7.8</b> A   |
| Nominal power      | <b>1.8</b> KVA |
| Maximum power      | <b>2.0</b> KVA |
| DC Output, Voltage | <b>12</b> Vdc  |
| DC Output, Amps    | <b>8.3</b> A   |

##### MOTOR

Type **4T OHV**

|                        |                                |
|------------------------|--------------------------------|
| Displacement           | <b>79.7</b> cm <sup>3</sup>    |
| Starter                | <b>Manual</b>                  |
| Max. power             | <b>2.6</b> HP                  |
| Fuel capacity (Petrol) | <b>4</b> L                     |
| Oil capacity           | <b>350</b> ml                  |
| Range                  | <b>6</b> h                     |
| Sound power level      | <b>62</b> dB (A)               |
| Dimensions             | <b>48 x 28.5 x 46</b> cm       |
| Weight                 | <b>18</b> Kg                   |
| Outputs                | <b>x1 Single-phase + 1 USB</b> |

#### INCLUDED

- Connector cable for DC output.
- Spare spark plug.
- Screwdriver.
- Spark plug spanner.
- Oil drain tube.



PROFESSIONAL QUALITY  
[www.stayer.es](http://www.stayer.es)